pantos	Ò
--------	---

Driver's Aid RECEIVER RC-448

SPECIFICATIONS

Specifications are subject to change without prior notice.

Specifications are subject to change without prior houce.							
			•				
Rev.	DATE	Revi			Revision history	ChangeNo.	Rep.
Create		September 22, 2017		2, 2017	PANTOS CO., LTD.		
Revision					FANTOS CO., ETE	J.	
Text	1 pages	Writing	Check	Approve	Document number		Rev.
Figure	2 sheets	Kumeki	Miura	Miura	RC448-00-0001		
Cover	1 sheet		iviiura	iviiura	110448-00-0001		

1. Outline

This remote control unit is a radio formula and is used combining the receiver. Two types of wireless and wired are prepared, so you can choose according to the installation environment,

A direct function does not assign to each switch of the RC-448, but a function is performed by choosing the key-menu displayed on a screen.

This remote control unit can perform all functions, without using the operation switch of the receiver.

Since this remote control unit omits taking measure against low and high temperature, be careful of employment,

2. Specifications

lh	Specifications					
ltem	Wired	Wireless				
Model	RC-448(01)	RC-448(02)				
Operation switch	Push button switches 7 pieces + 1 pieces ① OPTION-1					
Power supply switch		Slide switch (ON/OFF/Battery check)				
Radio(reception)		Received frequency 920MHz frequency band Transmission output 10mV Receiving distance Approx, 10m (Depending on usage conditions)				
Power supply		AA batteries 2 pieces				
Battery life		Approx, 6 months (It changes in the state of use)				
Environment of operation	Temperature $0 \sim 40^{\circ}\text{C}$ Humidity $20 \sim 80\%\text{RH}$ (No dew condensation)					
Preservation environment	Temperature $-20\sim60^{\circ}\mathrm{C}$ Humidity $10\sim85\%\mathrm{RH}$ (No dew condensation)					
External dimensions	74(W) ×216(H) ×52(D)mm (Projection things are not included.) Refer to appearance figure (RC448-00-0012)	74(W)×216(H)×52(D)mm (Projections · Wireless antenna not included,) Refer to appearance figure (RC448-00-0011D)				
Mass	Approx, 800g					
Accessories	Cable for connection to RC-441 1 %1	Antenna 1 AA batteries 2				

^{%1} The length of attached cable is negotiated for each installation site.



